

MOTOR AND PHASE ROTATION INDICATOR

KPS-CF100



- ☐ Phase sequence indicator in three-phase systems
- ☐ Determination of the direction of rotation of motors
- ☐ Indication of the rotating field without contact
- ☐ Indication of open phases
- ☐ Light indicators
- ☐ Integrated test leads
- ☐ Overvoltage category: CAT.III 600V



KPS-CF100

MOTOR AND PHASE ROTATION INDICATOR

General	
Power Supply	1x9V 6F22 Battery
Product Size	130mm×72mm×32mm
Product Weight	252g
Certification	CE/ETL
Safety Rating	CAT III 600V

Specs	
Nominal Voltage Rotary Direction	1~400V AC
Nominal Voltage Phase Indication	120~400V AC
Frequency	2~400Hz
Test Currents (In per phase)	Less than 3.5 mA
Built-in test leads	✓
Operating TEMP	0~40°C
Operating Altitude	2000m
Pollution Degree	2
Relative Humidity	15~80%RH

Product Code Information	
SKU	KPSCF100CBINT
EAN code	8435394747491
UPC code	810053670590
Pcs/export carton	20